

S E R V I C E N O T E

SUPERSEDES: NONE

70900A Local Oscillator**Serial Numbers:** 0000A00000 / 3049A02763**Fractional N Replacement Kits****Parts Required:** 70900-60206 or 70900-60211 or 70900-60207 or 70900-60212**Situation:**

The 70900-60125 A7A2 assembly in the 70900-60022 Fractional N Assembly is being obsoleted.

Solution/Action:

The kit to order depends on which controller board is in the 70900A. The controller board needs to be a MEM ++. This can be checked via the front panel softkeys. Under the Extend State softkey after the letters "CPU" it will have "68020" and after the letters "FPU" it will have "present". This denotes a MEM ++ Controller Board.

If the 70900A has a MEM ++ Controller Board and the RAM/ROM board is a standard (.25 MB board) then order the 70900-60207 Fractional N Kit. If the 70900A has a MEM ++ Controller Board and Option 512 (1 MB of RAM) then order the 70900-60212 Fractional N Kit Option 512.

If the 70900A doesn't have a MEM ++ Controller Board and the RAM/ROM board is a standard (.25 MB board) then order the 70900-60206 Fractional N & Controller Kit. If the 70900A doesn't have a MEM ++ Controller Board but does have Option 512 (1MB of RAM) then order the 70900-60211 Fractional N & Controller Kit Option 512.

DATE: October 1996

ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:

INFORMATION ONLY

AUTHOR:

ENTITY:

ADDITIONAL INFORMATION:

RDS

5340